

HDMI TO DIGITAL TV MODULATOR

MOD100



Watch your CCTV as a digital TV Channel anywhere in your home!



Features

- ✓ HD 1080p Digital Modulator
- ✓ Easy To Use Menu Controls
- ✓ A/V In - DVB-T RF Out
- ✓ USB Upgrade Port
- ✓ Backlit LCD Screen
- ✓ Aspect Ratio 16:9 & 4:3
- ✓ HDMI - DVB-T RF Out
- ✓ 203 x 120 x 52mm inc Bracket

Description

Most homes still use a co-ax as a way to distribute TV signals from the aerial to the various TVs within the property. The new MOD100 modulator allows you to make the best out of this set up and use it to distribute your home CCTV through this same co-ax network.

It works by allowing the HDMI output of a DVR (or other equipment such as a Satellite box) to be converted into a digital RF signal or 'Digital TV channel' so you can distribute it around a home and watch it on any TV just like it was a real digital TV channel.

Disclaimer

The technical specifications contained are given in good faith as being accurate but due to a continued program of improvement may change from time to time without notice. We apologise for any inconvenience due to changes of specification or errors and omissions within this document. Copyright

HDMI TO DIGITAL TV MODULATOR

MOD100



The MOD100 produces a high quality 1080p picture far superior to an analogue modulated signal and as all new TVs contain a digital tuner it's a great way to distribute CCTV in a home or a commercial building via co-ax.

Because the HDMI input to the MOD100 also carries sound and video, any connected TVs will also be able to playback sound from the DVR or other device too.

The MOD100 is also extremely useful for distributing the output from DVRs to multiple 'TVs' in commercial environments such as pubs or clubs as it can all be done over low cost co-ax using an off the shelf RF distributor.

Disclaimer

The technical specifications contained are given in good faith as being accurate but due to a continued program of improvement may change from time to time without notice. We apologise for any inconvenience due to changes of specification or errors and omissions within this document. Copyright

HDMI TO DIGITAL TV MODULATOR

MOD100



Specifications

No of Inputs	3
Input Connection	HDMI, Phono & RF Sockets
Audio Inputs	2
Audio Input Connection	HDMI & Phono
No of Outputs	1
Output Connection	RF Socket
Loop Throughs	1x RF
RF Output	142.5~946 MHz
Display	LCD
Power	12V DC
PSU	Supplied
Mount	Wall
Dimensions	203 x 120 x 52mm inc Bracket

Disclaimer

The technical specifications contained are given in good faith as being accurate but due to a continued program of improvement may change from time to time without notice. We apologise for any inconvenience due to changes of specification or errors and omissions within this document. Copyright